

**LISTING OF THE CLAIMS**

1-28. (canceled).

29. (previously presented) A machine-implemented method, comprising:  
 receiving a multimedia signal having data values;  
 forming the data values into a matrix of inputs [X];  
 forming a matrix [A] of predetermined values and multiplication operations;  
 factoring [A] into a butterfly matrix [B], a shuffle matrix [S], and a multiplication matrix [M], wherein the multiplication operations are selectively positioned into pairs within [M]; and  
 executing a Single Instruction Multiple Data (SIMD) instruction that multiplies [X], [B], [S], and [M] together to obtain a matrix of outputs [Y].

30. (Previously Presented) The machine-implemented method of claim 29, wherein the SIMD instruction is a Packed Multiply and Add (PMADDWD) instruction.

31. (Previously Presented) The machine-implemented method of 30, wherein values within [B] and [S] are integers selected from the group consisting of 1, 0 and -1.

32. (Previously Presented) The machine-implemented method of claim 31, wherein [A] is a 4-point Discrete Cosine Transform (DCT) transformation matrix, [X] represents a time domain of a video signal, and [Y] represents a frequency domain of the video signal.

33. (Previously Presented) The machine-implemented method of claim 32, wherein the multiplication matrix [M] is

$$\begin{bmatrix} \frac{1}{\sqrt{2}} & \frac{1}{\sqrt{2}} & 0 & 0 \\ \frac{1}{\sqrt{2}} & -\frac{1}{\sqrt{2}} & 0 & 0 \\ 0 & 0 & \cos(\frac{3\pi}{8}) & \cos(\frac{\pi}{8}) \\ 0 & 0 & -\cos(\frac{\pi}{8}) & \cos(\frac{3\pi}{8}) \end{bmatrix}$$

and wherein the positioned pairs are  $\frac{1}{\sqrt{2}}$  and  $\frac{1}{\sqrt{2}}$  and  $\frac{1}{\sqrt{2}}$  and  $-\frac{1}{\sqrt{2}}$ .

34. (Previously Presented) A machine-readable medium having instructions to cause a machine to perform a machine-implemented method, comprising:

- receiving a multimedia signal having data values;
- forming the data values into a matrix of inputs [X];
- forming a matrix [A] of predetermined values and multiplication operations;
- factoring [A] into a butterfly matrix [B], a shuffle matrix [S], and a multiplication matrix [M], wherein the multiplication operations are selectively positioned into pairs within [M]; and
- executing a Single Instruction Multiple Data (SIMD) instruction that multiplies [X], [B], [S], and [M] together to obtain a matrix of outputs [Y].

35. (Previously Presented) The machine-readable medium of claim 34, wherein the SIMD instruction is a Packed Multiply and Add (PMADDWD) instruction.

36. (Previously Presented) The machine-readable medium of claim 35, wherein values within [B] and [S] are integers selected from the group consisting of 1, 0 and -1.

37. (Previously Presented) The machine-readable medium of claim 36, wherein [A] is a 4-point Discrete Cosine Transform (DCT) transformation matrix, [X] represents a time domain of a video signal, and [Y] represents a frequency domain of the video signal.

38. (Previously Presented) The machine-readable medium of claim 37, wherein the multiplication matrix [M] is

$$\begin{bmatrix} \frac{1}{\sqrt{2}} & \frac{1}{\sqrt{2}} & 0 & 0 \\ \frac{1}{\sqrt{2}} & -\frac{1}{\sqrt{2}} & 0 & 0 \\ 0 & 0 & \cos(\frac{3\pi}{8}) & \cos(\frac{\pi}{8}) \\ 0 & 0 & -\cos(\frac{\pi}{8}) & \cos(\frac{3\pi}{8}) \end{bmatrix},$$

and wherein the positioned pairs are  $\frac{1}{\sqrt{2}}$  and  $\frac{1}{\sqrt{2}}$   
 $\frac{1}{\sqrt{2}}$  and  $-\frac{1}{\sqrt{2}}$ .

39. (Previously Presented) A system comprising:  
 a processing unit coupled to a memory through a bus; and  
 a process executed from the memory by the processing unit to cause the processing unit to:

receive a multimedia signal having data values;  
 form the data values into a matrix of inputs [X];  
 form a matrix [A] of predetermined values and multiplication operations;  
 factor [A] into a butterfly matrix [B], a shuffle matrix [S], and a multiplication matrix [M], wherein the multiplication operations are selectively positioned into pairs within [M]; and  
 execute a Single Instruction Multiple Data (SIMD) instruction that multiplies [X], [B], [S], and [M] together to obtain a matrix of outputs [Y].

40. (Previously Presented) The system of claim 39, wherein the SIMD instruction is a Packed Multiply and Add (PMADDWD) instruction.

41. (Previously Presented) The system of claim 40, wherein values within [B] and [S] are integers selected from the group consisting of 1, 0 and -1.

42. (Previously Presented) The system of claim 41, wherein [A] is a 4-point Discrete Cosine Transform (DCT) transformation matrix, [X] represents a time domain of a video signal, and [Y] represents a frequency domain of the video signal.

43. (Previously Presented) The system of claim 42, wherein the multiplication matrix [M] is

$$\begin{bmatrix} \frac{1}{\sqrt{2}} & \frac{1}{\sqrt{2}} & 0 & 0 \\ \frac{1}{\sqrt{2}} & -\frac{1}{\sqrt{2}} & 0 & 0 \\ 0 & 0 & \cos(\frac{3\pi}{8}) & \cos(\frac{\pi}{8}) \\ 0 & 0 & -\cos(\frac{\pi}{8}) & \cos(\frac{3\pi}{8}) \end{bmatrix},$$

and wherein the positioned pairs are  $\frac{1}{\sqrt{2}}$  and  $\frac{1}{\sqrt{2}}$   
 $\frac{1}{\sqrt{2}}$  and  $-\frac{1}{\sqrt{2}}$ .

44. (New) The method of claim 29, wherein the butterfly matrix [B] is of the form

$$\begin{bmatrix} 1 & 0 & 0 & 1 \\ 0 & 1 & 1 & 0 \\ 0 & 1 & -1 & 0 \\ 1 & 0 & 0 & -1 \end{bmatrix}.$$

45. (New) The machine-readable medium of claim 36, wherein the butterfly matrix [B] is of the form

$$\begin{bmatrix} 1 & 0 & 0 & 1 \\ 0 & 1 & 1 & 0 \\ 0 & 1 & -1 & 0 \\ 1 & 0 & 0 & -1 \end{bmatrix}.$$

46. (New) The system of claim 41, wherein the butterfly matrix [B] is of the form

$$\begin{bmatrix} 1 & 0 & 0 & 1 \\ 0 & 1 & 1 & 0 \\ 0 & 1 & -1 & 0 \\ 1 & 0 & 0 & -1 \end{bmatrix}$$